



Create the style you desire

Salon Airstylist Control

What look do you want today? The Salon Airstylist Essential has three versatile styling attachments and 400W of power so you can get creative with your hairstyles.

Create your own hairstyle

- · Volume and shine
- · Waves and curls
- · Loose curls

Retractable bristles make styling easy

· Retractable bristles for tangle free curls

Swivel cord

· For hassle-free use

2 heat settings

· To set your style

Airstyler HP4653/01

Highlights

Waves and curls



Waves and curls

Loose curls



Loose curls

Volume and shine

Volume and shine

Retractable bristles

Retractable bristles for tangle free curls

To set your style

To set your style

For hassle-free use

For hassle-free use

Specifications

Technical specifications

Cord length: 200 m Voltage: 220-240~ V Power: 400 W

Color/finishing: Silver/gray metalic

Frequency: 50-60 Hz Material housing styler: ABS

Features

Two heat settings: To set your style the way

you want

400 W: To deliver quick and easy results

Three attachments: To create your own style

Weight and dimensions

Net product dimensions excl. attachments:

475x258x220 mm

F-box dimensions: 230x60x200 mm A-box dimensions: 475x258x220 mm Weight of net product incl. attachements:

420 g

Number of F-boxes in A-box: 8

F-box weight (including product): 580 g

F-box volume: 2760 cm³ A-box weight: 500 g A-box volume: 26961 cm³

Attachments

Retractable bristle brush: For tangle free

waves & curls

Large vent brush: For loose curls Mixed bristle brush: For volume & shine

Pallet

Number of layers: 8 Quantity: 1200x800x1904 Number of carton per layer: 384

Serviceability

Replacement

Logistic data

Country of origin: PRC

EAN F-box: See pacdoc for your country

12NC code: 884465301000

EAN A-box: See pacdoc for your country

© 2022 Koninklijke Philips N.V. All Rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. or their respective owners.

Issue date 2022-08-12 Version: 2.1.1

