

# PHILIPS



D-Line Display

Signage Solutions

86"

Powered by Android

500cd/m<sup>2</sup>



86BDL4550D

## Chasing innovation

powered by Android

Amaze your guests with a smarter, faster, signage display. With integrated WiFi and designed for running Android apps, it's the next evolution in signage solutions

### Expand your viewing experience

- ADS wide-view panel display

### Innovative solutions for any signage application

- Save and play content with internal memory
- Android SoC processor. Native and web apps
- Integrated dual-band WiFi

### Care about you, your business and your audience

- SmartPower for energy saving
- Keep your content up and running with FailOver
- Ensure your content is running with automatic screenshots

### Maximizing the impact of your message

- CMND: Take control of your displays
- Manage settings of multiple displays with CMND & Control
- Create and update content with CMND & Create
- Connect and control your content via the cloud

## Highlights

### Powered by Android 8

Control your display via an Internet connection. Android-powered Philips Professional Displays are optimized for native Android apps, and you can install web apps directly to the display too. A new Android 8 ensures the software is kept secure and remain to the latest specification for longer.

### Internal Memory



Save and play content with internal memory. Upload your media into the display and playback content immediately. Working in conjunction with the internal browser, it also serves as a memory cache when streaming online content. If the network ever fails, the internal memory keeps content running by playing a cached version of the content, ensuring that your media stays up even if the network goes down.

### Proof of Play

Content is king, and with the automatic screenshot feature, you can make sure that your content is up and running at all times. Screenshots are taken throughout the day, which are then stored in the FTP server. From there, the screenshots can be viewed no matter when, or where you are.

### FailOver



Keeping your content up and running is critical for demanding commercial applications. While it is unlikely you will face a content disaster, FailOver provides content protection with a revolutionary technology that plays back-up content on screen in the event of a media player failure. FailOver automatically kicks in when the primary input fails. Simply select a primary input connection and a FailOver connection and your ready for instant protection.

### SmartPower



The backlight intensity can be controlled and pre-set by the system to reduce the power consumption by up to 50%, which saves substantially on energy costs.

### CMND



A robust display management platform, CMND puts the power back into your hands. Update and manage content with CMND & Create or control your settings with CMND & Control. It's all possible with CMND.

### CMND & Create



Design and create compelling content with CMND & Create, a powerful authoring tool. With a drag and drop interface, preloaded templates, and integrated widgets, you'll be able to amaze your customers with compelling content. Available in portrait and landscape mode.

### CMND & Control



With CMND & Control, easily manage multiple displays in a central location. With real time display monitoring, setting and software updates from a remote location, and the ability to customize and configure multiple displays at once, such as video wall or menu board displays, controlling your suite of displays has never been easier.

### ADS wide-view panel display

Be seen from any angle with ADS wide-view technology. Advanced Super Dimension Switch delivers faster on-display picture processing for smoother content transitions, remarkable image accuracy, and superior colour reproduction with 180 degree viewing.

### SmartBrowser

Connect and control your content via the cloud with the integrated HTML5 browser. Using the Chromium based browser, design your content online and connect a single display, or your complete network. Show content in both landscape and portrait mode, with fullHD resolution. Simply connect the display to the internet using WiFi or with an RJ45 cable, and enjoy your own created playlists.

# Specifications

## Picture/Display

**Diagonal screen size (metric):** 217.4 cm  
**Diagonal screen size (inch):** 85.6 inch  
**Aspect ratio:** 16:9  
**Panel resolution:** 3840 x 2160  
**Pixel pitch:** 0.4935 x 0.4935 mm  
**Optimum resolution:** 3840 x 2160 @ 120Hz  
**Brightness:** 500 cd/m<sup>2</sup>  
**Display colors:** 1.07 Billion  
**Contrast ratio (typical):** 1200:1  
**Dynamic contrast ratio:** 500,000:1  
**Response time (typical):** 8 ms  
**Viewing angle (horizontal):** 178 degree  
**Viewing angle (vertical):** 178 degree  
**Picture enhancement:** 3/2 - 2/2 motion pull down, 3D Combfilter, Motion compens. deinterlacing, 3D MA deinterlacing, Dynamic contrast enhancement, Progressive scan  
**Panel technology:** IPS  
**Operating system:** Android 8.0

## Connectivity

**Audio output:** 3.5mm jack  
**Video input:** Display Port 1.2 (x1), DVI-I (x 1), HDMI 2.0 (x3), USB 2.0 (x2)  
**Audio input:** 3.5 mm jack  
**Other connections:** OPS  
**Video output:** DisplayPort 1.2 (x1), HDMI 2.0 (x1)  
**External control:** RJ45, RS232C (in/out) 2.5 mm jack, IR (in/out) 3.5 mm jack  
**WiFi:** dual antenna 2,4Ghz and 5Ghz  
**4G/LTE antenna connectors:** mPCIe

## Convenience

**Placement:** Landscape (24/7), Portrait (24/7)  
**Tiled Matrix:** Up to 10 x 15  
**Screen saving functions:** Pixel Shift, Low Bright  
**Keyboard control:** Hidden, Lockable  
**Signal loop through:** IR Loopthrough, DisplayPort, HDMI, RS232  
**Energy saving functions:** Smart Power  
**Network controllable:** RS232  
**WiFi protocol:** a b g n, 802.1x

## Sound

**Built-in speakers:** 2 x 10W RMS

## Power

**Mains power:** 100 ~ 240 VAC, 50 ~ 60 Hz  
**Consumption (Typical):** 410 W  
**Consumption (Max):** 600 W  
**Standby power consumption:** <0.5 W  
**Energy Label Class:** G

## Supported Display Resolution

**Computer formats:** 1920 x 1080, 60Hz, 1280 x 1024, 60Hz, 1024 x 768, 60Hz, 1280 x 720, 60Hz, 1440 x 900, 60 Hz, 1600 x 900, 60Hz, 1680 x 1050, 60Hz, 3840 x 2160, 30, 60Hz, 640 x 480, 60Hz, 800 x 600, 60Hz  
**Video formats:** 1080p, 50, 60Hz, 1080i, 50, 60Hz, 2160p, 24, 30, 60Hz, 480i, 60Hz, 480p, 60Hz, 576i, 50Hz, 576p, 50Hz, 720p, 50,60 Hz

## Dimensions

**Set Width:** 1929.0 mm  
**Product weight:** 50.4 kg  
**Set Height:** 1100 mm  
**Set Depth:** 69.5(D@Wall mount) / 91.8(D@Handle) mm  
**Set Width (inch):** 75.94 inch  
**Set Height (inch):** 43.31 inch  
**Wall Mount:** 600(H)x400(V) mm, M8  
**Set Depth (inch):** 2.74(D@Wall mount) / 3.61(D@Handle) inch  
**Bezel width:** 15.5 mm (Even bezel)  
**Product weight (lb):** 111.11 lb

## Operating conditions

**Altitude:** 0 ~ 3000 m  
**Temperature range (operation):** 0 ~ 40 °C  
**MTBF:** 50,000 hour(s)  
**Temperature range (storage):** -20 ~ 60 °C  
**Humidity range (operation)[RH]:** 20 - 80% RH (No condensation)  
**Humidity range (storage) [RH]:** 5 - 95% RH (No condensation)

## Multimedia Applications

**USB Playback Video:** MPEG, H.263, H.264, H.265  
**USB Playback Picture:** BMP, JPEG, PNG  
**USB Playback Audio:** AAC, HEAAC, MPEG

## Internal Player

**CPU:** 2 x A53 + 2 x A73  
**GPU:** ARM Mali G51  
**Memory:** 3GB DDR  
**Storage:** 32 GB eMMC

## Accessories

**Included accessories:** Quick start guide, RS232 cable, AC Power Cord, IR sensor cable (1.8M), Remote Control & AAA Batteries  
**Included Accessories:** RS232 daisy-chain cable, Philips logo (x1), AC Switch Cover, USB Cover (x1), Screws

## Miscellaneous

**On-Screen Display Languages:** English, French, German, Spanish, Polish, Turkish, Russian, Italian, Simplified Chinese, Traditional Chinese, Arabic, Japanese, Danish, Dutch, Finnish, Norwegian, Portuguese, Swedish  
**Warranty:** 3 year warranty  
**Regulatory approvals:** CE, RoHS, BSMI, CB, CCC, CU, EMF, ETL, FCC, Class A, PSB, VCCI, J-Moss, PSE

Philips 86BDL4550D  
 Version 1.0  
 Release Date: 20200908

