

Philips Internal Bulk Drive, SATA

DVD-ROM

SPD2216BM

Simply superior performance

The name to trust for reliability

Philips innovative technology enables DVD data to be read at 16x speed, and it can read and play all DVD and CD formats with the stability you expect.

Superior Performance

• Maximum DVD reading speed at 16X

Convenience

• Plug & Play for easier installation



Specifications

Reading Speed

- DVD-ROM: 16x (21600 kB/s)
- CD-ROM: 48x (7200 kB/s)
- Access time: 110 ms
- Buffer size: 256 kB

Connectivity

• Interface: SATA interface

Convenience

• Ease of Installation: Plug & Play

Power

- Power consumption: 18 W
- Power input: DC 5V 1.2A / 12V 1A

System Requirements

- PC OS: Microsoft Windows® 7, Vista, XP, 2000
 SP4
- Processor: Pentium 4 1.3GHz or higher
- RAM memory: 256 MB
- Hard disk space: 500 MB

Technical specifications

- Operating temperature range: +5 ... +50 $^{\circ}\text{C}$
- \bullet Storage temperature range: -40 ... +65 $^{\circ}\text{C}$
- Humidity: 20 ... 80 %RH (no condensation)
- Safety standards: EN60950, EN60825EMC standards: EN55022, EN55024

Product dimensions

- Product dimensions (W \times H \times D): 14.82 \times 4.2 \times 17 cm
- Weight: 0.75 kg

Packaging dimensions

- EAN: 87 12581 54158 3
- Packaging type: Bulk

Outer Carton

- Outer carton (L \times W \times H): 37.8 \times 31.7 \times 23.8 cm
- Gross weight: 9.5 kg
- Nett weight: 7.5 kg
- · Tare weight: 2 kg
- EAN: 87 12581 54160 6
- Number of consumer packagings: 10







Issue date 2014-03-14

Version: 1.1.1

© 2014 Koninklijke Philips N.V. All Rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. or their respective owners.

12 NC: 8670 000 62758 EAN: 87 12581 54158 3

www.philips.com

Highlights

16X reading speed on DVD ROM

According to industry standards this drive reads at maximum 16X with highest stability.

Plug & Play

Plug & Play gives you the ability to install or add a new component and have it work without having to perform any complex installation procedure or technical analysis.