



# Designed by installers, made by Philips

Ultra-thin with a stunning 7.1 cm/2.8" QVGA color touch screen the Pronto TSU9300 is a hybrid of full functionality! It can blend into practically any modern interior with its designer looks and geometric aluminum and black gloss finishing.

#### A touch of elegance

- High resolution 2.8" color touchscreen with superb contrast
- Ergonomic design for single-handed operation
- Cutting-edge design with flush-mounted display

#### **Personalized convenience**

- User interface matching your personal taste and preferences
- Control multiple devices with a single touch
- · Control hidden equipment and devices in other rooms

#### Music, mood and ambiance

- · Music server control with intuitive rotary cursor
- Pre-configured lighting control (Lutron RadioRa)
- Access digital files from any Windows MCE PC



## Specifications

#### **Picture/Display**

- Diagonal screen size (inch): 2.8 inch
- Display colors: 65,536
- Resolution: 320 x 240 pixels
- Display screen type: LCD TFT
- Touch panel

#### Connectivity

- Connector: Mini USB
- Power: 100-240V, 50/60Hz
- Built-in wireless technology: 802.11g
- Encryption / security: WEP 128 bit, WEP 64 bit
- Network mode: DHCP, Fixed IP
- USB: USB 2.0

#### Convenience

#### · Automatic power off

- Multi language: English, Spanish, French, German, Dutch
- Clock with calendar
- Cradle/ docking station
- Cursor key
- · Pick up sensor
- · Rotary wheel

#### **Accessories**

- AC/DC Adaptor
- · CD-ROM
- Docking Station
- Printed User Guide
- USB cable

### System Requirements

- Hard disk space: 250 MB free
- PC OS: Windows XP, Vista
- CD-ROM drive
- RAM memory: 256 MB free
- USB: Free USB port

#### Power

- · Battery capacity: 1700 mAh
- Charging time: Up to 3.5 hr
- Battery Type: LI-Polymer
- On/Off switch

#### Customization

- · Full screen configurability
- · Alpha-blending
- Macros: Up to 250 steps
- Database: Configurable personal database, Model number based database

#### System Specifications

- CPU: Freescale 32 bit RISC
- CPU speed: 266 MHz
- Ram size: 64 MB

#### **Infrared Capabilities**

- Operating distance: 36 ft (12 m)
- Learning IR codes
- Transmitting LEDs: 5
- Universal IR code database
- Number of brands in database: Over 3000

#### **RF** Capabilities

- Frequency (GHz): 2.4
- WiFi based

#### **Outer Carton**

- EAN: 69 23410 70183 8
- Gross weight: 1 kg
- Outer carton (L  $\times$  W  $\times$  H): 35.5  $\times$  21.6  $\times$  10 cm
- Nett weight: 0.604 kg
- Number of consumer packagings: 1
- Tare weight: 0.396 kg

#### **Packaging dimensions**

- Packaging dimensions (W x H x D):
- 21.6 x 35.5 x 10 cm
- EAN: 69 23410 70183 8
- · Gross weight: 1 kg
- Nett weight: 0.604 kg
- Number of products included: 1
- Packaging type: Carton
- Tare weight: 0.396 kg
- Type of shelf placement: Laying

#### **Product dimensions**

- Product dimensions (W  $\times$  H  $\times$  D):
- 10 x 15.7 x 3.4 cm
- Weight: 0.295 kg

### Highlights

#### Customizable UI

User interface can be created to fully incorporate the end user's personal taste and preferences. So, only the devices and buttons that are used most, will be visible on the touchscreen. Also, the graphical design (backgrounds, icons, buttons, colors used) can be chosen by the user.

Flush-mounted display Flush-mounted display means that the screen is not recessed anymore, but instead flows smoothly with the casing.

#### Music server control

Out-of-the-box, a user can control his music server e.g. Escient Fireball. The user interface of the music server is built into the remote control. It facilitates listening to music without being in view of a TV, which is normally required to display a music server's user interface. This, in combination with an ergonomic thumb wheel on the remote, simplifies selecting tracks and playlists, & also frees up the TV screen for other activities.

#### Lighting control

Pre-configured lighting control includes a full onscreen user interface for controlling lighting scenes, moods and individual dimmers. With on-screen feedback from lighting throughout the house, the end user knows if the light is actually on or off.

#### **MCE PC** functionality

Through 3rd party software, the Pronto control panel can incorporated Windows MCE PC functionality. This means you are able to access any digital files from your MCE PC via the control panel.

#### **One-touch convenience**

One-touch control allows you to perform multiple commands with one press of a button via a macro. A macro combines a string of pre-programmed commands under one single button. Therefore, it simply takes one button press to execute a series of functions.

#### **Extended control**

A range of extenders is available, both wired and wireless versions, that extend the range of transmission of the remote control. This enables the user to control equipment hidden in cabinets or in other rooms with one and the same control unit.



Issue date 2013-01-31

12 NC: 8670 000 63304 EAN: 69 23410 70183 8 © 2013 Koninklijke Philips Electronics N.V. All Rights reserved.

www.philips.com

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.

Version: 2.0.4